



(Ex) II 1/2G Ex d ia IIC T6...T1 GA/Gb

Order-No: V1757546/001

Radarsensor 4 ... 20 mA - VEGAPULS 61

The radar sensor VEGAPULS 61 from Vega for continuous level measurement of liquids provides high accuracy regardless of pressure, temperature, gas and dust (also in Zone 1+2 according to ATEX). The device is wear- and maintenance-free and available in various materials with protection up to IP 67 (optional IP 68 (1 bar)).









Powerful

- High accuracy (also zone 1+2 according to ATEX)
- · contactless measuring
- easy to install
- wear- and maintenance-free
- Measurement independent of the pressure, temperature, gas and dust

Reliable sensor

The VEGAPULS 61 emitted extremely short microwave pulses to the surface of the measured medium and evaluates the reflected pulses (via internal antenna system). The special evaluation procedure ensures a reliable and accurate measurement.

Easy operation


The device is easy to operate and parameterize via VEGACONNECT 4 (optional) and the PC software (PACTware).

The adjustment of the instrument for operation on-site is carried out via the optional module PLICSCOM or via a PC with the adjustment software PACTware and respective DTM.

Technical data:	Mlog Rada	r-Senso	r VEGAF	PULS 61
ATEX label	II 1/2G Ex d ia IIC T6T1 GA/Gb			
Operating voltage	9.6 30 V DC			
Signal output	4 20 mA / HART 2-wire			
Enclosure Rating	IP 66/67 (optional IP 68)			
Dimension (ØXH);	115 mm x 283 mm (4.53" x (11,14") with b		14") with bracket	
Function Principle	Micro wave pulse			
Temperature	Process Ambient / storage	_	C + 80 °C C + 80 °C	(-40°F+176°F) (-40°F+176°F)
Pressure	Operation:	-1+	+2 bar	-100 +200 kPa
Measuring range	up to 35 m	114,8 ft		
Deviation	± 2 mm			
Mlog connection intrinsically safe sensor connection	Uo 15,8V; lo	48 mA;	Lo 50mH	
Max. values:	Ui = 30 V Ii =	= 131 mA	Pi = 983 m\	W.

Further information about the product http://www.vega.com

Manager Software



ORI reserve the right to change any information without notice. - Error and omission expected.